



CYCLOPS LIGHTING

CPX 160

DMX CHART

DMX control mode

MODE3 CHANNELS		
Channel	Value	Function
1	000 - 255	HUE
2	000 - 255	Saturation
3	000 - 255	Value

MODE 8 CHANNELS		
Channel	Value	Function
1	000 - 255	Dimmer
2	001 - 063	Dimmer Curve1
	064 - 127	Dimmer Curve2
	128 - 191	Dimmer Curve3
	192 - 255	Dimmer Curve4
3	001 - 005	No fuction
	006 - 049	Dimmer speed 1
	050 - 099	Dimmer speed 2
	100 - 149	Dimmer speed 3
	150 - 199	Dimmer speed 4
	200 - 255	Dimmer speed 5
4	000 - 255	Red
5	000 - 255	Green
6	000 - 255	Blue
7	000 - 255	White
8	000 - 255	Strobe

MODE 12 CHANNELS		
Channel	Value	Function
1	000 - 255	Dimmer
2	001 - 063	Dimmer Curve1
	064 - 127	Dimmer Curve2
	128 - 191	Dimmer Curve3
	192 - 255	Dimmer Curve4
3	001 - 005	No fuction
	006 - 049	Dimmer Curve1
	050 - 099	Dimmer Curve2
	100 - 149	Dimmer Curve3
	150 - 199	Dimmer Curve4
	200 - 255	Dimmer Curve5

4	000 - 255	Red
5	000 - 255	Green
6	000 - 255	Blue
7	000 - 255	White
8	000 - 255	Strobe
9	000 - 255	color
10	000 - 255	CCT
11	000 - 255	Auto 1-13
12	000 - 255	speed slow -fast

MODE 32 CHANNELS		
Channel	Value	Function
1	000 - 255	Led1 Red
2	000 - 255	Led1 Green
3	000 - 255	Led1 Blue
4	000 - 255	Led1 White
5	000 - 255	Led2 Red
6	000 - 255	Led2 Green
7	000 - 255	Led2 Blue
8	000 - 255	Led2 White
9-12	000 - 255	Led3 RGBW
13-16	000 - 255	Led4 RGBW
17-20	000 - 255	Led5 RGBW
21-24	000 - 255	Led6 RGBW
25-28	000 - 255	Led7 RGBW
29-32	000 - 255	Led8 RGBW

MODE 37 CHANNELS		
Channel	Value	Function
1	000 - 255	Dimmer
2	001 - 063	Dimmer Curve1
	064 - 127	Dimmer Curve2
	128 - 191	Dimmer Curve3
	192 - 255	Dimmer Curve4
3	001 - 005	No fuction
	006 - 049	Dimmer speed 1
	050 - 099	Dimmer speed 2
	100 - 149	Dimmer speed 3
	150 - 199	Dimmer speed 4
	200 - 255	Dimmer speed 5
4	000 - 255	Auto 1-13
5	000 - 255	speed slow -fast/strobe
6	000 - 255	Led1 Red
7	000 - 255	Led1 Green
8	000 - 255	Led1 Blue
9	000 - 255	Led1 White
10	000 - 255	Led2 Red
11	000 - 255	Led2 Green
12	000 - 255	Led2 Blue
13	000 - 255	Led2 White

14-17	000 - 255	Led3 RGBW
18-21	000 - 255	Led4 RGBW
22-25	000 - 255	Led5 RGBW
26-29	000 - 255	Led6 RGBW
30-33	000 - 255	Led7 RGBW
34-37	000 - 255	Led8 RGBW