

CYCLOPS

LIGHTING

SPARK ONE

DMX CHART

Channel (CH)	Value Range	Function
CH1: Safety / Heating	0-10	Pre-heat OFF
	11-220	Emergency Stop (E57)
	221-239	Cleaning Mode (CLE)
	240-255	Pre-heat ON (0-500)
CH2: Output Level	0-15	OFF
	16-39	Level 1 (F1)
	40-63	Level 2 (F2)
	64-87	Level 3 (F3)
	88-111	Level 4 (F4)
	112-135	Level 5 (F5)
	136-159	Level 6 (F6)
	160-183	Level 7 (F7)
	184-207	Level 8 (F8)
	208-231	Level 9 (F9)
232-255	Level 10 (F10)	